



# Health Care Facilities Code • 2012 edition changed from a "Standard" to a "Code" • What does that mean? — A code tells you what you have to do — A standard tells you how to do it — A code is in mandatory language and can typically be adopted into law more readily






# New and existing facilities • NFPA 99 does not have occupancy chapters or specific chapters for new and existing facilities. • At the beginning of each chapter, items that apply to existing facilities are identified.

# Example from Chapter 6 6.1\* Applicability. 6.1.1 This chapter shall apply to new health care facilities as specified in Section 1.3. Dedicated to optimizing the health care physical structurers.


|  | • |
|--|---|
|  |   |
|  |   |
| <b>6.1.2</b> The following paragraphs of this chapter  |   |
| shall apply to   |   |
| new and existing health care facilities: (1) 6.3.2.2.4.2   |   |
| (2) 6.3.2.2.6.1  |   |
| (3) 6.3.2.2.6.2(F)   |   |
| Etc  |   |
| ASHE Descrited to optimizing the   |   |
| Dedicated to optimizing the health care physical environment.  American Inspiral American Inspiral American Inspiral |   |
|  |   |
|  |   |
|  |   |
|  |   |
|  |   |
| • <b>6.1.3</b> Paragraph 6.3.2.2.3 shall apply only to   |   |
| existing facilities.   |   |
|  |   |
|  |   |
|  |   |
|  |   |
|  |   |
| ASHE Dedicated to optimizing the health care physical environment. American Hesphal                                  |   |
| Autodati   |   |
|  |   |
|  |   |
|  | 1 |
| Most inspection, testing and maintenance   |   |
| requirements apply to new and existing facilities.   |   |
| is sinces.   |   |
| Most requirements for documentation apply to   |   |
| new and existing facilities.   |   |
|  |   |
|  |   |
|  |   |
| ASHE Designated to optimizing the  |   |


1.3.2.3 An existing system that is not in strict compliance with the provisions of this code shall be permitted to be continued in use, unless the authority having jurisdiction has determined that such use constitutes a distinct hazard to life.


Dedicated to optimizing the health care physical environment.



















## Central supply systems cylinder storage


(5.1.3.2.3 & 5.1.3.2.4)

- Only cylinders, reusable shipping containers and accessories allowed in room
- No flammable materials, gases or liquids in the room

(ASHE) d to optimizing the health care physic

## Location of central/bulk supply equipment

- Indoor locations (5.1.3.3.2(4))
  - 1-hour fire resistance rating of the enclosure
  - Non-combustible or limited combustible finishes
- New in the 2012 edition
- Outdoor installations require 2 entry/exits (5.1.3.3.2 (3))





## Securing cylinders

- 2002 Individually secure all cylinders
- 2005 –Secure all cylinders
- 2012 "...secure all cylinders from falling..."

5.1.3.3.2(7)



ASHE






| Master Alarms<br>(5.1.9.2)   |
|--|
| Two separate alarm panel locations required  1. An area of continuous operation  2. In the office or workspace of the individual responsible system maintenance  • A BAS system can be used for one of the two master alarm locations if it meets the NFPA 99 requirements |
| ASHE Dedicated to optimizing the health care physical environment. American Hospital   |







# Examples of requirements easily overlooked Evaluate the capacity of bulk systems annually Testing flexible connectors Examples: The hose on relocatable med gas and/or vacuum outlets in headwall systems Ceiling booms containing med gas and/or vacuum outlets Permanent retention of installation and verification documentation Nitrogen purge audible alarm when brazing




# Chapter overview 6.1 Application 6.2 Nature of Hazards 6.3 Electrical system 6.4 Essential Electrical Systems - Type 1 6.5 Essential Electrical Systems - Type 2 6.6 Essential Electrical Systems - Type 3

# Acronyms EPSS – Essential Power Supply System EPS – Emergency Power Supply EES – Essential Electrical System AHJ – Authority Having Jurisdiction FGI Guidelines – Facility Guidelines Institute Guidelines for the Design and Construction of Health Care Facilities








## Access to overcurrent protective devices Added language in NFPA 99-2012 Category 1 and 2 rooms Only authorized personnel have access to overcurrent protective devices Overcurrent protective devices not permitted to be located in public access space Isolated power panels can be in critical care areas


d to optimizing the health care physic


(ASHE)

### Minimum number of receptacles NFPA 99-2012 NFPA 99-2005 Use or area Patient bed locations - general care areas Patient bed locations - critical areas 14 Operating rooms (Category 1) Not specified Not required Special rooms (examples -psychiatric, pediatric, hydrotherapy) Outlets with 2 or 4 receptacles, or an equivalent power strip every 1.6 to 3.3 feet in instrument use areas Outlets with 2 or 4 receptacles, or an equivalent power strip every 1.6 to 3.3 feet in instrument use areas Laboratories Receptacles in designated general care pediatric locations, other than nurseries shall be listed as tamper resistant or shall have a tamper resistant cover d to optimizing the health care physic ASHE

|   | Minimum number of receptacles   |
|---|---|
| ŀ | FGI Guidelines Table 2.1-3  • More detailed than NFPA 99  • Includes minimum number of receptacles as well as guidance regarding the location |
|   | ASHE Dedicated to optimizing the health care physical environment.  American Inspir   |







### Wet procedure locations - special protection NFPA 99-2005 NFPA 99-2012 Special protection required Special protection required 1. Power distribution system 1. Power distribution system that inherently limits the that inherently limits the possible ground fault current possible ground fault current to a low value with out to a low value with out interrupting the power (such interrupting the power (such as an isolated power system) as an isolated power system) 2. Power system that interrupts 2. Power system that interrupts the supply of power if the the supply of power if the fault current exceeds 6 ma fault current exceeds the trip (such as a GFCI) value of a Class A GFCI (trip between 4 ma and 6 ma) ASHE

# Wet locations —existing construction Wet location protection not required if the following are met: Written inspection procedure acceptable to the AHJ is enforced by an individual at the health facility Equipment grounding conductors for 120-V single phase 15 and 20 amp receptacles, connected equipment and fixed equipment are installed and maintained as per NFPA 70, National Electrical Code

Wet procedure locations —existing construction Inspection and testing instead of protection

• Electrical continuity test of of all required equipment, grounding conductors and their connections

• Test frequency

— When first installed

— Where there is evidence of damage

— After any repairs

— At intervals not exceeding 6 months

## Battery power lights

- One or more provided in locations where deep sedation or general anesthesia is performed
- Sensor unit connected to the branch circuit providing lighting in the room
- Provide lighting for 90 minutes
- Tested monthly for 30 seconds and annually for 30 minutes

ASHE > Dedicated to optimizing the health care physical environment.

## Maintenance and testing of electrical systems

Where hospital grade receptacles are required at patient bed locations and in locations where deep sedation or anesthesia occurs, test receptacles after installation, replacement or servicing.

Additional testing interval defined by performance data

ASHE Dedicated to optimizing the health care physical environment.

## Electrical receptacles

### Testing

- Physical integrity
- Continuity of grounding
- Correct polarity
- Retention force of the grounding blade



ASHE Dedicated to optimizing the health care physical environment.

## Maintenance and testing of electrical systems Non-hospital grade receptacles in patient bed locations and in locations where deep sedation or general anesthesia takes place –

test at intervals not exceeding 12 months.

ASHE

dicated to optimizing the

## Line isolation monitor (LIM) testing

Monthly activate test switch

Test can be performed at not more than 12 month interval if the LIM has a self calibration feature

ASHE

sted to optimizing the health care physical environment.







|   | ASHE On-Line E-learning Courses  |
|---|--|
|   | Application of NFPA 99 in Health Care Facilities   |
|   | Electrical Systems for Health Care Facilities  |
|   | ASHE On-Demand Webinars  |
|   | http://www.ashe.org/education/ondemand.shtml Chapter 43 of 101 Impact on Health Care Facilities CMS and 2012 LSC – Planning your Compliance Strategy Focus on Compliance |
| 1 | ASHE Descrited to optimizing the health care physical environment.  American Host  |